SPT - Surge Protection Tester



Product Specifications

Model	SPT-02
MOV Test	
Measuring Range	5 - 1020 VDC
Voltage Accuracy	±3%
GDT Test	
Measuring Range	5 - 1020 VDC
Voltage Accuracy	±3%
Voltmeter	
DC Voltage	0 - 950 V
AC Voltage	0 - 700 V
Resolution	1 V
Voltage Accuracy	±3%
Insulation Resistance	
Test Voltage	250 V, 500 V, 1000 V
Measuring Range	$\begin{array}{l} 250 \ V \rightarrow 0.2 \ M\Omega \ - 2 \ G\Omega \\ 500 \ V \rightarrow 0.2 \ M\Omega \ - 4 \ G\Omega \\ 1000 \ V \rightarrow 0.2 \ M\Omega \ - 8 \ G\Omega \end{array}$
Accuracy	$\begin{array}{l} 0.2 \ M\Omega - 4 \ G\Omega \rightarrow \pm 3 \ \% \\ 4 \ M\Omega - 8 \ G\Omega \rightarrow \pm 5 \ \% \end{array}$
Short Circuit Current	1.2 mA
Polarisation Index (PI)	on all ranges
Detective Absorbtion Ratio (DAR)	on all ranges
Diode Test	
Test Voltage	5 VDC
Max. Test Current	1.5 mA
Measurement Voltage	0 - 4.5 V
Accuracy	±3 %

Novaris has a policy of continuing product development, therefore specifications are subject to change without notice. Copyright: © 2015 Novaris Pty Ltd

Multifunction Surge Protection Tester

Use the Novaris Surge Protection Tester to monitor and diagnose Novaris products without built in visual indication.

Voltage Clamping and Switching tests

Voltage clamping devices such as Metal Oxide Varistors or Silicon Avalanche Diodes are rated by their breakdown voltage. The SPT-02 applies an increasing voltage until 1mA of current flows through the clamping component.

Voltage switching devices such as Spark Gaps or Gas Discharge Tubes are rated by their firing voltage. The SPT-02 applies an increasing voltage until it registers the short circuit produced by the arc.

These values are presented on the 2 x 16 character display until the next test is performed.

Multifunction

Other test modes supported include insulation resistance to $8G\Omega$ at up to 1000V, voltmeter, diode testing and resistance testing from 0.01Ω to $400k\Omega$.

Portable

The SPT-02 is designed with portability in mind. The unit comes it a carry case and is powered by 6 x AA batteries.

Model	SPT-02
Continuity	
Ranges	0.01 - 100 Ω 100 - 300 Ω 300 - 1999 Ω
Accuracy	$\begin{array}{l} 0.01 - 100 \ \Omega \rightarrow \pm \ 1.0 \ \% \\ 100 - 300 \ \Omega \rightarrow \pm \ 1.5 \ \% \\ 300 - 1999 \ \Omega \rightarrow \pm \ 2.0 \ \% \end{array}$
Auto Null	up to 5 Ω
Buzzer	up to 3 Ω
kΩ Test	
Ranges	1- 400 kΩ
Short Circuit Test Current	≥ 1.3 mA
General	
Fuse	500 mA 250 V Fast Blow
Display	2 Line x 16 Character LCD
Dimensions	205 mm x 90 mm x 55 mm (L x W x D)
Power Source	1.5 V AA x 6
Storage Temperature	-20 to +70 °C
Weight	1.5 kg
Customs Tariff	85354010
Accessories	Test Leads Fuse (0.5 A 250V) Heavy Duty Case Instruction Manual Batteries
Standards	EN 61010-1 CATIII 600 V EN 61326-1



72 Browns Road, Kingston Tasmania 7050 Australia Phone +61 3 6229 7233 Fax +61 3 6229 9245 E-mail sales@novaris.com.au